



## SAFETY INSTRUCTIONS

2. Equipment should be mounted securely in locations and at heights where it will not be readily subjected to tampering by unauthorized personnel. 3. Do not mount near gas or electric heaters. 4. Cap unused wires with enclosed wire nuts or other approved method. 5. Do not use this equipment for anything other than its intended use. 6. The use of accessory equipment not recommended by the manufacturer will void product listing and warranty and may cause an unsafe condition. 7. Use caution when servicing batteries. 8. Any service on this equipment should be performed by qualified personnel only. 9. Make sure wire terminations are secure and leads are properly tucked in appropriate wire channels. **CONSULT A QUALIFIED ELECTRICIAN BEFORE INSTALLING**




### Caution:


Disconnect AC power before servicing and installation. All electrical connections must be in accordance with NEC/CEC or your local code.

## SURFACE MOUNTED WITH J-BOX


**1.** Loosen and remove the side M4 screws which used to fix the mounting plate.




**2.** Fix the mounting plate to the ceiling with the screws.



**3.** Connect the clip on the fixture to the spindle of the mounting plate to make sure the fixture will not slip and fall. Connect the line voltage to the wires coming out from the fixture following the wiring diagram. Push the pressing plate into the suspension loop on the mounting plate.



**4.** Lock the M4 screws to complete the installation.



## PENDANT WITH 3/4" CONDUIT

**1.** Connect the line voltage to the wires coming out from the fixture following the wiring diagram.

Wire Color	Line	Neutral	Ground
Black	○	○	○
White	○	○	○
Green/Yellow Green	○	○	○
Purple	○	○	○
Gray	○	○	○

Note: Two dimming wires are in the driver box.

**2.** Screw the fixture to the 3/4 inch conduit to complete the installation.

