

LET-250-12V-AC

DESCRIPTION: This quiet 250W-120V electronic step-down transformer is designed to be used with low voltage lighting systems and is protected against overload, short circuit and over heat and has a 4 year guarantee.

SPECIFICATIONS:

INPUT	120V 60Hz
OUTPUT AT MAX. LOAD	11.5V 40kHz
MAXIMUM LOAD	250W
MINIMUM LOAD W/O DIMMER	50W
MINIMUM LOAD WITH DIMMER	50W
INPUT CURRENT AT MAXIMUM LOAD	2.1A
OUTPUT CURRENT AT MAXIMUM LOAD	21A
POWER FACTOR MIN.	0.95
DIMMABLE	✓
AVAILABLE COLORS:	
● BLACK ○ WHITE	



MAGNETIC TRANSFORMER

DESCRIPTION: Transformers are UL- and CUL-listed for use with lighting fixtures. These transformers are for use with 120/240 VAC/60 Hz input. The 24/12 volt secondary outputs are protected by inherent resettable breakers. The appropriate transformer can easily be determined by multiplying the number of lamps by the watts per lamp. For larger transformers (ODX-750S, ODC-750S, ODX-1000 and ODX-1200X), consideration should be given to the maximum capacity of each fused output. Capacities shown are conservative underestimates by approximately 10%.



CAT#	Type	Output(12v)	Output(24v)	Depth	Height	Width	Weight
EV24-150	Magnetic	1@150 watts	1@150 watts	2-15/16"	7-9/16"	3-1/16"	10 lbs.
EV24-200	Magnetic	1@200 watts	1@200 watts	2-15/16"	7-9/16"	3-1/16"	12 lbs.
ODC-250S	Magnetic	1@250 watts	1@250 watts	3-3/8"	8-1/16"	4-3/16"	16 lbs.
ODX-250S-24	Magnetic	-----	1@250 watts	3-3/8"	8-1/16"	4-3/16"	16 lbs.
EV24-300	Magnetic	1@300 watts	1@300 watts	3-3/8"	8-1/16"	4-3/16"	16 lbs.
ODX-500	Magnetic	2@250 watts	1@300 watts	4-1/4"	9-7/16"	4-11/16"	20 lbs.
ODX-600S	Magnetic	2@300 watts	1@500 watts	4-1/4"	9-7/16"	4-11/16"	20 lbs.
ODC-750S	Magnetic	3@250 watts	1@600 watts	4-1/4"	9-7/16"	4-11/16"	28 lbs.
ODX-750S-24	Magnetic	-----	2@375 watts	4-1/4"	9-7/16"	4-11/16"	28 lbs.
ODX-1000	Magnetic	4@250 watts	2@500 watts	5-7/16"	10-9/16"	6-3/4"	35 lbs.
ODX-1200S	Magnetic	4@300 watts	2@600 watts	5-7/16"	10-9/16"	6-3/4"	35 lbs.