


## LET-60

**DESCRIPTION:** This quiet 60W-12V electronic step-down transformer is designed to be used with low voltage lighting systems and is protected against overload, short circuit and over heat and has a 2 year guarantee.

### SPECIFICATIONS:

INPUT	120V 60HZ
OUTPUT AT MAX. LOAD	11.5V 40KHZ
MAXIMUM LOAD	60W
MINIMUM LOAD	20W
INPUT CURRENT AT MAXIMUM LOAD	0.5A
OUTPUT CURRENT AT MAXIMUM LOAD	5A
POWER FACTOR	0.95
MAXIMUM HARMONIC DISTORTION	14.8%
DIMMABLE	✓
ALUMINUM CASING	✓




## LVT-60

**DESCRIPTION:** This quiet 60W-12V electronic step-down transformer is designed to be used with low voltage lighting systems and is protected against overload, short circuit and over heat and has a 2 year guarantee.

### SPECIFICATIONS:

INPUT	120V 60HZ
OUTPUT AT MAX. LOAD	11.5V 40KHZ
MAXIMUM LOAD	60W
MINIMUM LOAD	20W
INPUT CURRENT AT MAXIMUM LOAD	0.5A
OUTPUT CURRENT AT MAXIMUM LOAD	5A
POWER FACTOR MIN.	0.95
MAXIMUM HARMONIC DISTORTION	14.8%
DIMMABLE	✓
ALUMINUM CASING	✓
WATERPROOF POTTING	✓



## LET-201

**DESCRIPTION:** This quiet 200W-12V electronic step-down transformer is designed to be used with low voltage lighting systems and is protected against overload, short circuit and over heat and has a 2 year guarantee.

### SPECIFICATIONS:

INPUT	120V 60HZ
OUTPUT AT MAX. LOAD	11.7V 29KHZ
MAXIMUM LOAD	200W
MINIMUM LOAD	50W
INPUT CURRENT AT MAXIMUM LOAD	1.7A
OUTPUT CURRENT AT MAXIMUM LOAD	17A
POWER FACTOR MIN.	0.98
MAXIMUM HARMONIC DISTORTION	10%
DIMMABLE	✓
ALUMINUM CASING	✓
WATERPROOF POTTING	✓

