



APPLICATION:

- Bathrooms
- Stairwells
- Residential
- Commercial/hospitality

PRODUCT FEATURES:

- Wall or ceiling mount
- Supplied with smooth white acrylic diffuser
- Diffuser easily removed via locking nut at both ends of fixture
- Standard multi-volt ballast
- Chrome end caps
- CEE qualified ballast comes standard on most fixture options (Consult factory for details)

PRODUCT OPTIONS

- Rocker switch
- Pull chain switch

LISTING

UL/C-UL listed to US and Canadian standard

WARRANTY

Guaranteed for one year against mechanical defects

T8
OVLM

Fluorescent Surface Mount Vanity

Ordering Information > Example: 4-OVLM-2-32-T8-ADV-10-MVOLT-EMG-T8-BX-700



FIXTURE SIZE	SERIES	WATTAGE	VOLTAGE ¹	# OF BALLAST	BALLAST FACTOR
4 - 4'	OVLM-Oracle Fluorescent Vanity Light Mounting	4' FIXTURE 1-32-T8 (1 lamp/32W/T8) 2-32-T8 (2 lamps/32W/T8)	(Blank)- MVOLT (120/277) 120 277 347	(Blank)- 1 Ballast 2- 2 Ballasts	(Blank)- Normal BF

BALLAST CONFIGURATION & CODE			
17W/T8	25W/T8	32W/T8	DESCRIPTION
(Blank)	-	(Blank)	Electronic Instant Start
EPS	(Blank)	EPS	Electronic Program Start
ADV-7	-	ADV-7	Advance Mark-7 ¹
ADV-10	-	ADV-10	Advance Mark-10 ¹
-	-	-	Advance Optanium ¹
ADV-ESS	-	ADV-ESS	Advance Essential ¹
ADV-ROVR	-	ADV-ROVR	Advance Rover ¹
-	-	LUT-EHD	Lutron Ecosystem H-Series ¹
-	-	LUT-2W	Lutron Tu-Wire ¹
LUT-EC5	LUT-EC5	LUT-EC5	Lutron Ecosystem ¹
LUT-EC3	LUT-EC3	LUT-EC3	Lutron Eco-10 ¹
-	-	LUT-TVE	Lutron Tve ¹
LUT-H3D	LUT-H3D	LUT-H3D	Lutron Hi-Lume 3D ¹
-	-	-	Lutron Ecosystem (347V Only) ¹

¹ - Voltage must be specified for dimming ballast.

EMERGENCY BATTERY PACK OPTIONS (L. = LUMENS)	
ORDER CODE	DESCRIPTION
EMG-T8-BX-450	Up to 450 L. for T8 or BX
EMG-T8-BX-600	Up to 600 L. for T8 or BX
EMG-T8-BX-700	Up to 700 L. for T8 or BX
EMG-T8-BX-1400	Up to 1400 L. for T8 or BX
EMG-SD-T8-BX-T5-T5HO-1400	Self-Diagnostic 1400 L. for T8, BX, T5 or T5HO
EMG-ICE-T8-BX-T5-T5HO-1400	ICE Pack 1400 L. for T8, BX, T5 or T5HO
GTD	Generator Transfer Device

WIRING OPTIONS	
FBF	- Internal Fast Blow Fuse
SBF	- Internal Slow-Blow Fuse
RIS	- Radio Interference Suppressor

OTHER OPTIONS	
RS	- Rocker Switch
PCS	- Pull Chain
USA	- Made in America Compliance