





### **L:** 9-3/8"

#### **W:** 1-5/8"

#### **H:** 1-7/16"

# **HEAVY DUTY 24V 300W TRANSFORMER**

## **DESCRIPTION**

This quiet 300W-24V electronic step-down transformer is designed to be used with low voltage lighting systems and is protected against overload, short circuit and over heat and has a 4 year guarantee. This transformer is offered with three 1/2" KO's and is designed for branch circuit and remote applications.

TECHNICAL SPECIFICATIONS			
INPUT	120V 60Hz		
OUTPUT AT MAX. LOAD	23.5V 40kHz		
LOAD	50-300W		
OUTPUT AT	300W/24V. 23.5V 30kHz		
INPUT CURRENT AT	300W 2.5A		
OUTPUT CURRENT AT	300W 24V. 13.3A		
POWER FACTOR MIN.	0.985		
MAXIMUM HARMONIC DISTORTION	24V 2.3%		
DIMMABLE			
ALUMINUM INNER CASING			
STEEL OUTER CASING			
WATER-PROOF POTTING UL94VO	<b>✓</b>		

SPECIFIED BY:	TYPE:	JOB NAME:

