




## LP-LGC-FL-SPC-1

**Lumi-PRO** Extrusion/FLOOR




#### **Lumi-PRO Extrusion SPECIALTY/FLOOR**

**Designed for floor applications**, our Floor-Optimized LED Extrusion provides a sophisticated lighting solution that seamlessly combines practicality with aesthetic appeal. **This specialized extrusion is meticulously crafted to meet the unique requirements of floor installations** within various interior design spaces.


The installation of our **Lumi-Pro Extrusion/Floor** is a hassle-free process, requiring minimal effort. The extrusion seamlessly merges with the floor surface, creating a clean and polished appearance. **Utilizing screws or clips**, the installation process is straightforward, eliminating the need for intricate procedures.

Designed specifically for use with our **LB series LED Light Strips**, these extrusions offer a versatile and customizable lighting solution for distinct recessed spaces within **residential, commercial, or hospitality** settings.



1.MOQ (minimum order quantity) required for these options, please consult factory.

#### Compatible LB Series-24V LED Strip Light










# LP-LGC-FL-SPC-1 Lumi-PRO Extrusion/FLOOR

#### DIMENSIONS



#### MOUNTING







Mounting the profile directly using screws without the need for clips.

#### **OPTICAL LENSES**



#### END CAPS/INCLUDED



2 Waterproof end caps INCLUDED

2 End Caps With Holes INCLUDED
2 End Caps Without Holes INCLUDED



Apply UV sealant to the waterproof endcap layer to achieve IP65-rated protection.

UV sealant not provided.

FTD - Flat Diffuser INCLUDED

It Can be ordered in 3 different ways.

### 1. Everything will be shipped separately

#### RL

• Channel, cover, accessories and tape light will be cut and shipped to your desired length.





Accessories if ordered.



#### 2. Pre-assembled and shipped separately as two units

#### PA

- Channel, cover, accessories and tape light will be cut and shipped to your desired length.
- Cover, end caps and clips will be assembled to the channel.
- Wiring accessories will be attached to the tape light.





Wiring accessories attached to the tape light.

#### 3. Fully assembled and shipped as a single unit

#### FA

- Channel, cover, accessories and tape light will be cut and shipped to your desired length.
- Wiring accessories will be attached to the tape light.
- Tape light will be installed into the channel and ready to use.











## COMPATIBLE TAPE LIGHT Ordering Guide

Power feed, jumpers and connectors compatible with this channel

	LB1000-MN	LB1000-LR	LB1000-ST	LB1000-ST-HO	LB1000V-ST	LB1003-ST	LB1000-ST-SC	LB1004-ST
Soldered Lead (SL)	<b>✓</b>	<b>✓</b>	<b>✓</b>	✓	<b>✓</b>	<b>√</b>	<b>✓</b>	✓
Soldered Jumper (JPSL)	✓	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>
Power Connector (TW)	X	X	X	X	X	X	Х	X
Tape Connector (TT)	X	X	X	Х	X	X	X	X
Tape Jumper (JP)	X	X	X	X	X	X	Х	X
Closed End (CE)	✓	<b>✓</b>	<b>✓</b>	✓	<b>✓</b>	<b>√</b>	<b>✓</b>	<b>√</b>
DC Connector Male- (DCM)	<b>✓</b>	<b>√</b>	<b>√</b>	✓	<b>√</b>	✓	<b>√</b>	<b>√</b>
DC Connector Female-(DCF)	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>

Power feed, jumpers and connectors compatible with this channel

	LB3000-ST	LB3000-ST-HE	LB3000-FC-ST	LB3000-TWH	LB4000-RGB	LB3000-RGBW	LB4000-RGBTWH	LB4000-RGBW
Soldered Lead (SL)	<b>✓</b>	<b>✓</b>	<b>✓</b>	<b>✓</b>	<b>√</b>	<b>✓</b>	<b>√</b>	<b>✓</b>
Soldered Jumper (JPSL)	<b>√</b>	✓	✓	✓	<b>√</b>	✓	<b>√</b>	<b>√</b>
Power Connector (TW)	<b>✓</b>	<b>√</b>	<b>√</b>	<b>√</b>	X	<b>√</b>	X	X
Tape Connector (TT)	<b>✓</b>	<b>√</b>	<b>√</b>	<b>✓</b>	X	<b>√</b>	X	X
Tape Jumper (JP)	<b>✓</b>	<b>√</b>	<b>√</b>	<b>√</b>	X	<b>√</b>	X	X
Closed End (CE)	<b>✓</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>✓</b>	<b>√</b>
DC Connector Male- (DCM)	<b>√</b>	✓	✓	✓	✓	✓	<b>√</b>	<b>√</b>
DC Connector Female-(DCF)	<b>✓</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>	<b>√</b>

SL= Soldered Lead JPSL= Soldered Jumper DCM=DC Connector Male soldered DCF=DC Connector Female soldered TW=Tape to Wire Power Feed TT=Tape to Tape Connector JP=Jumper Wire for Connectors CE=Closed end no connector



Not compatible with this channel.

NOTE: The endcap hole should be enlarged to allow wiring to pass through, or the channel may be used without endcaps.





## LP-LGC-FL-SPC-1

**Lumi-PRO** Extrusion/FLOOR Refer to the tape light spec sheet for detailed information.

## COMPATIBLE TAPE LIGHT Ordering Guide

Power feed, jumpers and connectors compatible with this channel

	1 own lood, jumpore and competible with the char							une ondinion
	LB1000-WL-ST	LB3000-RGBW Wet-Location	LB1000-WDM					
Soldered Lead (SL)	✓	✓	✓					
Soldered Jumper (JPSL)	<b>✓</b>	<b>√</b>	<b>√</b>					
Power Connector (TW)	X	Х	Х					
Tape Connector (TT)	X	X	X					
Tape Jumper ( <b>JP)</b>	X	X	Х					
Closed End (CE)	✓	<b>✓</b>	<b>&gt;</b>					
DC Connector Male- (DCM)	<b>✓</b>	<b>✓</b>	<b>√</b>					
DC Connector Female-(DCF)	<b>√</b>	<b>√</b>	✓					

SL= Soldered Lead JPSL= Soldered Jumper DCM=DC Connector Male soldered DCF=DC Connector Female soldered
TW=Tape to Wire Power Feed TT=Tape to Tape Connector JP=Jumper Wire for Connectors CE=Closed end no connector



Not compatible with this channel.

NOTE: The endcap hole should be enlarged to allow wiring to pass through, or the channel may be used without endcaps.








## LP-LGC-FL-SPC-1

#### Lumi-PRO Extrusion/FLOOR

Refer to the tape light spec sheet for detailed information.




Series-LB1000-MN 280lm/ft - 2.9W/ft Indoor Strip Light Width / 0.16"/4mm







Series-LB1000-LR | 295lm/ft - 3.1W/ft |
Indoor Strip Light | Width / 0.39" /10mm | 37 LEDs/FT











RL - Rolls 16ft
PA - Pre-Assembled
FA - Fully Assembled






## LP-LGC-FL-SPC-1

#### Lumi-PRO Extrusion/FLOOR

Refer to the tape light spec sheet for detailed information.




Series-LB1000V-ST Indoor Strip Light Width / 0.39" / 10mm 73 LEDs/FT







500lm/ft - 3W/ft

Series-LB1003-ST Indoor Strip Light Width / 0.3"/ 8mm 55 LEDs/FT






Series-LB1000-ST-SC 1082lm/ft-7W/ft Indoor Strip Light Width / 0.3" / 8mm 61 LEDs/FT











FA - Fully Assembled

## LP-LGC-FL-SPC-1


### Lumi-PRO Extrusion/FLOOR

Refer to the tape light spec sheet for detailed information.




Series-LB3000-ST Indoor Strip Light Width / 0.3"/8mm 146 LEDs/FT

325lm/ft - 3W/ft






Series-LB3000-ST-HE | 940lm/ft-5.8W/ft Indoor Strip Light Width / 0.39" / 10mm 88 LEDs/FT





Series-LB3000-FC-ST |550lm/ft-4.6W/ft **Indoor Strip Light** Width / 0.39" / 10mm 98 LEDs/FT





Series-LB3000-TWH  $\mid$  520lm/ft - 6.1W/ft Indoor Strip Light Width / 0.39"/10mm 195 LEDs/FT

LB3000 **SERIES** WATTAGE LENGTH **TECHNOLOGY VOLTAGE** LB3000 6.1W - 6.1W/ft 16F - 16ft Roll TWH-65K-27K - TWH/6500K-2700K 24V - 24V TW10-3C - Power Connector C - Custom **SHIPPING OPTIONS** 

RL - Rolls 16ft PA - Pre-Assembled FA - Fully Assembled



WIRING ACCESSORIES

SL-3 - Soldered Lead JPSL-3 - Soldered Jumper

Tape to Tape Jumper

JP10-3C






## LP-LGC-FL-SPC-1

### Lumi-PRO Extrusion/FLOOR

Refer to the tape light spec sheet for detailed information.




Series-LB4000-RGB | 250lm/ft - 6.1W/ft Indoor Strip Light Width / 0.39" / 10mm 51 LEDs/FT





Series-LB3000-RGBW | 255lm/ft - 6.1W/ft Indoor Strip Light Width / 0.47"/12mm 256 LEDs/FT




RL - Rolls 16ft PA - Pre-Assembled FA - Fully Assembled



Series-LB4000-RGBTWH Indoor Strip Light Width / 0.47"/12mm 18 LEDs/FT


**SERIES** LB4000

RL - Rolls 16ft PA - Pre-Assembled FA - Fully Assembled





Series-LB4000-RGBW | 250lm/ft - 5.9W/ft Indoor Strip Light Width /0.47"/12mm 18 LEDs/FT







## LP-LGC-FL-SPC-1

#### Lumi-PRO Extrusion/FLOOR

Refer to the tape light spec sheet for detailed information.




565lm/ft - 4.6W/ft

Outdoor Strip Light


72 LEDs/FT

Width / 0.53" / 13mm






Series-LB3000-RGBW 218lm/ft - 6.1W/ft
Outdoor Tape Light
Width / 0.55"/14mm
256 LFDs/FT





Series-LB1000-WDM | 515lm/ft - 4.4W/ft | Indoor Tape Light | Width / 0.47"/12mm | 51 LEDs/FT



FA - Fully Assembled